

PCE Americas Inc.
711 Commerce Way
Suite 8
Jupiter
FL-33458
USA
From outside US: +1
Tel: (561) 320-9162
Fax: (561) 320-9176
info@pce-americas.com

PCE Instruments UK Ltd.
Units 12/13
Southpoint Business Park
Ensign way
Hampshire / Southampton
United Kingdom, SO31 4RF
From outside UK: +44
Tel: (0) 2380 98703 0
Fax: (0) 2380 98703 o
jinfo@pce-instruments.com

www.pce-instruments.com/english www.pce-instruments.com

## Technical Clamp on Tester PCE-LCT 1

# Digital Clamp Meter to test leakage current / RMS measurement / continuity and resistance test / measures voltage up to 600 V

With the PCE-LCT 1 Clamp Meter it is possible to measure leakage currents up to a range of 100 A. PCE-LCT 1 Clamp Meter can measure leakage currents which appear when current flows through electrical conductors which are not designed for conduction current. The PCE-LCT 1 Clamp Meter can detect leakage currents and show them on the display. With the help of the PCE-LCT 1 Clamp Meter you can detect insulation failures in places where machines cannot be disconnected, however insulation must be checked, as for instance according to the VDE 701/702 standard. The PCE-LCT 1 Clamp Meter measures current flow, voltage up to 600 V, resistance and continuity. The PCE-LCT 1 is the ideal instrument for electricians according to the VDE standard. The PCE-LCT 1 has a compact design which allows to be placed in any pocket. The rubber protection protects the instrument against falls, so it is the ideal instrument to be used in electrical inspections and in workshops.

- Measures leakage current
- Measures current up to 100 A
- Measures voltage up to 600 V
- Continuity test
- Measures resistance up to 400  $\boldsymbol{\Omega}$
- Digital bar graph
- High resolution
- Max./min. values are viewed on the display
- Rubber protector
- Test cables are included

## **Technical Specifications**

#### Leakage current and current (AC A)

Measurement ranges	Resolution	Accuracy	
		50 / 60 Hz	400 Hz 1 kHz
40 mA	10 μΑ	± (1 % + 0,5 mA)	± (4,5 % + 0,5 mA)
400 mA	100 μΑ	± (3 % + 5 mA)	± (3 % + 5 mA)
4 A	1 mA	± (4 % + 0,1 mA)	± (4 % + 0,1 A)
40 A	10 mA	± (4 % + 1 A)	± (4 % + 1 A)
80 A	10 mA	± (2,5 % + 1 A)	± (3 % + 1 A)
80 A - 100 A	100 mA	± (5 % + 1 A)	± (5 % + 1 A)

## Voltage (AC V)

Measurement ranges Resolution Accuracy

50 / 60 Hz 400 Hz ... 1 kHz

400 V 1 V  $\pm$  (1,5 % + 2 digits)  $\pm$  (2 % + 4 digits)

Resistance

Measurement ranges Resolution Accuracy Alarm

 $400 \Omega$  0,1 Ω ± (1 % + 2 digits) Measurement value <38Ω

### **General Technical Specifications**

Display 3 3/4

Measured electrical properties AC V, AC A, resistance
Security standards CAT III 300 V / CAT II 600 V

 $\begin{array}{ll} \mbox{Diameter of the clip} & 30 \mbox{ mm} \\ \mbox{Input impedance} & 10 \mbox{ M}\Omega \end{array}$ 

Registration rate 2 Hz (numerical values), 20 Hz (bar graph)

Operating temperature -10 °C ... 50 °C
Operating humidity <85 % H.r.
Storing temperature -20 °C ... 60 °C
Auto shut-off after 30 minutes
Power 9 V battery
Input current 10 mA
Weight 200 g

Dimensions 210 x 62 x 35,6 mm

## **Delivery contents:**

1 x PCE-LCT 1 Clamp Meter

1 x 9 V battery 2 x test cables

1 x carrying case

1 x user's manual